

Belegungsplan der 37-pol. Sub-D-Stecker:

SPS-Eingänge	37-pol-Sub-D Stecker
E 10.0;	24
E 10.1;	23
E 10.2;	22
E 10.3;	21
E 10.4;	2
E 10.5;	3
E 10.6;	4
E 10.7;	5
E 11.0;	28
E 11.1;	27
E 11.2;	26
E 11.3;	25
E 11.4;	6
E 11.5;	7
E 11.6;	8
E 11.7;	9

SPS-Ausgang	37-pol-Sub-D Buchse
A 4.0;	24
A 4.1;	23
A 4.2;	22
A 4.3	21
A 4.4;	2
A 4.5;	3
A 4.6;	4
A 4.7;	5
A 5.0;	28
A 5.1;	27
A 5.2;	26
A 5.3;	25
A 5.4;	6
A 5.5;	7
A 5.6;	8
A 5.7;	9

+24 Spg-Versorg.	19/37
Masse GND	1/20
Frei	10,11,12,13,14,15,16, 17,18,29,30,31,32,33, 34,35,36

+24 Spg-Versorg.	19/37
Masse GND	1/20
Frei	10,11,12,13,14,15,16, 17,18,29,30,31,32,33, 34,35,36

Verdrahtung der Analog - Ein-/Ausgänge:

Analogeingang Kanal	Klemme	Analogausgang Kanal	Klemme
CH0 Spannung	3	CH0	17
CH1 Spannung	4	CH1	18
CH2 Spannung	7		
CH3 Spannung	10		
CH4 Widerstand	12/14 ; 13/15		